

Generator Change Over Switch

User Guide

V1: 17/04/2024

STEP 1

Ensure that all appliances/equipment within the dwelling/building are turned off i.e., air conditioners, stove, oven, kettle, fridges, freezers, pressure pumps. Your generator may not be large enough to operate some of these appliances.

STEP 2

In your switchboard, switch the generator change over switch down to the (II) position (GEN FEED) which indicates you have now changed from Mains to Generator power supply.

IMPORTANT NOTE:

You should hear 2 clicks

STEP 3

Ensure the GEN INLET protection switch is on by flicking the grey switch to the up position.

STEP 4

Before turning on the generator, ensure that your generator has sufficient fuel and oil and is placed in a dry location where it will have plenty of air circulation. Also check that your extension lead isn't damaged. i.e., cuts or exposed wires

STEP 5

Turn on the generator following the user manual specific to the make and model.

STEP 6

Plug the generator into the generator inlet.

STEP 7

Turn on essential appliances/equipment one at a time. i.e., fridges/freezers, pressure pump, lights

STEP 8

To change back to Mains power supply, flick the generator change over switch back up to the MAINS FEED position. Then power down generator.

